

Boundary Dimensions (mm)			Basic Dynamic Load Ratings (N) $C_r$	Limiting Loads (N) $P_{max}$	Limiting Track Loads (N)	Bearing Numbers	NSKHPS
$D$	$C$	$d$					
16	11	6	5800	2360	3350	FCR-16	
16	11	6	5800	2360	3350	F CRS-16	
16	11	6	2830	2360	3350	FCJ-16	
16	11	6	2830	2360	3350	FCJS-16	
19	11	8	6600	4200	4150	FCR-19	
19	11	8	6600	4200	4150	F CRS-19	
19	11	8	3450	4200	4150	FCJ-19	
19	11	8	3450	4200	4150	FCJS-19	
22	12	10	8550	6550	5300	FCR-22	
22	12	10	8550	6550	5300	F CRS-22	
22	12	10	4350	6550	5300	FCJ-22	
22	12	10	4350	6550	5300	FCJS-22	
26	12	10	8550	6550	6000	FCR-26	
26	12	10	8550	6550	6000	F CRS-26	
26	12	10	4350	6550	6000	FCJ-26	
26	12	10	4350	6550	6000	FCJS-26	
30	14	12	12500	9250	7800	FCR-30	
30	14	12	12500	9250	7800	F CRS-30	
30	14	12	7200	9250	7800	FCJ-30	
30	14	12	7200	9250	7800	FCJS-30	
32	14	12	12500	9250	8050	FCR-32	
32	14	12	12500	9250	8050	F CRS-32	
32	14	12	7200	9250	8050	FCJ-32	
32	14	12	7200	9250	8050	FCJS-32	
35	18	16	18600	17000	11800	FCR-35	
35	18	16	18600	17000	11800	F CRS-35	
35	18	16	9700	17000	11800	FCJ-35	
35	18	16	9700	17000	11800	FCJS-35	
40	20	18	20500	21700	14300	FCR-40	
40	20	18	20500	21700	14300	F CRS-40	
40	20	18	10300	21700	14300	FCJ-40	
40	20	18	10300	21700	14300	FCJS-40	
47	24	20	28200	26400	20800	FCR-47	
47	24	20	28200	26400	20800	F CRS-47	
47	24	20	19200	26400	20800	FCJ-47	
47	24	20	19200	26400	20800	FCJS-47	
52	24	20	28200	26400	22900	FCR-52	
52	24	20	28200	26400	22900	F CRS-52	
52	24	20	19200	26400	22900	FCJ-52	
52	24	20	19200	26400	22900	FCJS-52	
62	29	24	40000	38500	34000	FCR-62	
62	29	24	40000	38500	34000	F CRS-62	
62	29	24	24900	38500	34000	FCJ-62	
62	29	24	24900	38500	34000	FCJS-62	
72	29	24	40000	38500	38000	FCR-72	
72	29	24	40000	38500	38000	F CRS-72	

Boundary Dimensions (mm)			Basic Dynamic Load Ratings (N) $C_r$	Limiting Loads (N) $P_{max}$	Limiting Track Loads (N)	Bearing Numbers	NSKHPS
$D$	$C$	$d$					
<b>72</b>	29	24	24900	38500	38000	<b>FCJ-72</b>	
<b>72</b>	29	24	24900	38500	38000	<b>FCJS-72</b>	
<b>80</b>	35	30	60500	61000	52000	<b>FCR-80</b>	
<b>80</b>	35	30	60500	61000	52000	<b>FCRS-80</b>	
<b>80</b>	35	30	39000	61000	52000	<b>FCJ-80</b>	
<b>80</b>	35	30	39000	61000	52000	<b>FCJS-80</b>	
<b>85</b>	35	30	60500	61000	55500	<b>FCR-85</b>	
<b>85</b>	35	30	60500	61000	55500	<b>FCRS-85</b>	
<b>85</b>	35	30	39000	61000	55500	<b>FCJ-85</b>	
<b>85</b>	35	30	39000	61000	55500	<b>FCJS-85</b>	
<b>90</b>	35	30	60500	61000	59000	<b>FCR-90</b>	
<b>90</b>	35	30	60500	61000	59000	<b>FCRS-90</b>	
<b>90</b>	35	30	39000	61000	59000	<b>FCJ-90</b>	
<b>90</b>	35	30	39000	61000	59000	<b>FCJS-90</b>	